



Main

Product or component type	Industrial Control Transformer
Rated power in VA	500 VA
Primary voltage	240 x 480 V 230 x 460 V 220 x 440 V
Secondary voltage	120/240 V 115/230 V 110/220 V
Range of product	T

Complementary

Phase	1 phase
Rated power in VA	500 VA per UL 500 VA per CSA 500 VA per NOM 300 VA per CE
Primary voltage	220 x 440 V : 110/220 V 230 x 460 V : 115/230 V 240 x 480 V : 120/240 V
Temperature rise	115 °C
Electrical connection	Screw clamp terminals
Height	3.84 in
Width	4.5 in
Depth	5.49 in
Material	Copper winding
Product compatibility	FSC2

Environment

product certifications	CE UL listed file E61239 CSA file LR37055 guide 184-N-90
NEMA degree of protection	Not rated (open device)
insulation temperature	356 °F (180 °C)

Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 1227 - Schneider Electric declaration of conformity	Compliant - since 1227 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Need no specific recycling operations	Need no specific recycling operations
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Phenyl glycidyl ether, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Phenyl glycidyl ether, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

Contractual warranty

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

