



Main

| | |
|-----------------------------------|--------------|
| Product or component type | Load Center |
| Range of product | QO |
| Load center type | Main breaker |
| Line Rated Current | 100 A |
| Number of spaces | 16 |
| Short-circuit current | 22 kA |
| Number of circuits | 16 |
| Number of tandem circuit breakers | 0 |
| Phase | 1 phase |
| System Voltage | 120/240 V AC |

Complementary

| | |
|---------------------------|------------------------------------|
| AWG gauge | AWG 6...AWG 2/0 (aluminium/copper) |
| NEMA degree of protection | NEMA 3R outdoor |
| Cover type | Surface cover |
| Electrical connection | Lugs |
| Device composition | Grounding bar (ordered separately) |
| Electrical connection | Lugs |
| Wiring configuration | 3-wire |
| Material | Tin plated copper busbar |
| Enclosure material | Welded galvanized steel |
| Surface finish | Baked enamel grey |
| Box number | 4R |
| Product certifications | UL listed |
| Height | 22.05 in (560 mm) |
| Width | 14.76 in (375 mm) |

Environment

Offer Sustainability

| | |
|---|---|
| Not Green Premium product | Not Green Premium product |
| Compliant - since 1248 - Schneider Electric declaration of conformity | Compliant - since 1248 - Schneider Electric declaration of conformity |
| Reference not containing SVHC above the threshold | Reference not containing SVHC above the threshold |
| Need no specific recycling operations | Need no specific recycling operations |
| WARNING: This product can expose you to chemicals including: | WARNING: This product can expose you to chemicals including: |
| Lead and lead compounds which is known to the State of California to cause cancer and birth defects or other reproductive harm. | Lead and lead compounds which is known to the State of California to cause cancer and birth defects or other reproductive harm. |
| For more information go to www.p65warnings.ca.gov | For more information go to www.p65warnings.ca.gov |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.